King's Research Portal

DOI:

[10.1109/TCYB.2020.3024754](https://doi.org/10.1109/TCYB.2020.3024754)

Document Version

Early version, also known as pre-print

[Link to publication record in King's Research Portal](#)

Citation for published version (APA):

Zeng, Y., Lam, H. K., Xiao, B., & Wu, L. (Accepted/In press). I_2 - I Control of Discrete-Time State-Delay Interval Type-2 Fuzzy Systems via Dynamic Output Feedback. *IEEE Transactions on Cybernetics*.
<https://doi.org/10.1109/TCYB.2020.3024754>

Citing this paper

Please note that where the full-text provided on King's Research Portal is the Author Accepted Manuscript or Post-Print version this may differ from the final Published version. If citing, it is advised that you check and use the publisher's definitive version for pagination, volume/issue, and date of publication details. And where the final published version is provided on the Research Portal, if citing you are again advised to check the publisher's website for any subsequent corrections.

General rights

Copyright and moral rights for the publications made accessible in the Research Portal are retained by the authors and/or other copyright owners and it is a condition of accessing publications that users recognize and abide by the legal requirements associated with these rights.

- Users may download and print one copy of any publication from the Research Portal for the purpose of private study or research.
- You may not further distribute the material or use it for any profit-making activity or commercial gain
- You may freely distribute the URL identifying the publication in the Research Portal

Take down policy

If you believe that this document breaches copyright please contact librarypure@kcl.ac.uk providing details, and we will remove access to the work immediately and investigate your claim.

$\ell_2 - \ell_\infty$ Control of Discrete-time State-delay Interval Type-2 Fuzzy Systems via Dynamic Output Feedback

Yi Zeng, Hak-Keung Lam, *Fellow, IEEE*, Bo Xiao, Ligang Wu, *Fellow, IEEE*

Abstract—This paper investigates the design of $\ell_2 - \ell_\infty$ dynamic output feedback (DOF) controller for interval type-2 (IT2) T-S fuzzy systems with state delay. For nonlinear systems, IT2 fuzzy model is an efficient modeling method which can better express uncertainties than (type-1) fuzzy model. In addition, state delay is also a general factor that affects the system performance. After analyzing the stability of the system, based on convex linearization and the projection theorem, this paper proposes a delay dependent output feedback controller design method. The IT2 membership functions of fuzzy controller are chosen to be different from those of the model so as to increase the freedom of controller selection. A membership-function-dependent (MFD) method based on staircase membership functions (MFs) is applied to relax the stability analysis results. Finally, numerical simulation example is given to illustrate the effectiveness of the results.

Index Terms—output feedback control, state-delay IT2 fuzzy system, fuzzy-model-based system, discrete-time system

I. INTRODUCTION

As a high-efficient modeling method of nonlinear system, fuzzy model has received extensive attention from academia and industry. Since the (type-1) T-S fuzzy system was proposed [1], the research on fuzzy-model-based (FMB) system covers many fields and problems. Compared with non-fuzzy control methods, FMB control has demonstrated better performance in system modeling, system robustness and fault tolerance. [2], [3] focus on the dynamic control design of FMB systems, where the $\ell_2 - \ell_\infty$ performance and Hankel-norm performance were considered respectively. [4] suggested an application of the fuzzy PID controllers in robotic teleoperation which has notable prospects in telemedicine. Both [5] and [6] designed fuzzy logic control schemes to stabilize the chaotic systems. [7] and [8] offered observer-based fuzzy control schemes, in which the former was specially applied to the mechanical exoskeleton and the latter was mainly based on a new interpolation functions in design. [9], [10] studied the control design problem of sampled-data fuzzy systems. Among them, [9] designed a tracking controller, and [10] was mainly

designed for the vehicle suspension systems. In [11], [12], the MFD stability condition was obtained by approximating the original MFs with staircase MFs. Based on the above results, [13] study the stability condition and stabilization problem for state-delay FMB systems. [14] proposed a further relaxed stability condition for FMB system. Because of the existence of time delay in all kinds of systems, time delay is often considered when studying fuzzy systems. Based on a delay partitioning method, [15] considered the time delay of the fuzzy sampled-data systems. Some results about filter design for state-delay fuzzy systems can be found in [16], [17].

In the research of fuzzy model, researchers try to improve the fuzzy model to enhance the expression efficiency of the FMB systems to the actual nonlinear system. Type-1 fuzzy set can represent the nonlinear information of the system effectively, but it shows limitations in dealing with the uncertainty existing in the system [18]. IT2 T-S fuzzy model is to use the interval MFs to enhance the expression of uncertainty in the systems. In view of the inevitable uncertainty in industrial systems, taking account of the modeling of uncertainty can improve the robustness and control performance of actual industrial systems. Lam investigated the stability condition of IT2 T-S FMB control system for the first time, in which an initiative work is done for IT2 fuzzy modeling and controller design [19]. Extended from [19], Lam proposed an imperfect premise matching (IPM) controller and obtained relaxed stability conditions, where the IPM concept was first proposed in [20] that the issue due to the inherently mismatched MFs between IT2 fuzzy model and controller can be handled. In order to further utilizing the information in the IT2 MFs, Lam in [18] proposed a piecewise linearization based MFD method to further support the stability condition analysis. By introducing a novel performance index, [21] studied the output and state control for IT2 T-S FMB systems. In addition to the controller design problem of IT2 T-S FMB systems, other related problems have been studied recently. For networked IT2 T-S fuzzy systems, [22], [23] studied the filter design in the consideration of data packet dropouts and random link failures. For discrete-time IT2 T-S FMB systems, [24] proposed a method to solve model reduction problem. [25]–[27] are pioneering works investigated the stability condition of polynomial FMB control systems. [28] compared comprehensively the membership-function-independent/dependent methods for type-1 and IT2 FMB control systems. To utilize the information of MFs in the analysis, various MFD analysis techniques are proposed by Lam [29], which can be

This work was in part supported by King's College London and China Scholarship Council.(Corresponding Author: H.K. Lam)

Y. Zeng is with the Department of Engineering, King's College London, Strand, London ,WC2R 2LS, U.K. (e-mail: yi-zeng1991@outlook.com).

H.K. Lam is with the Department of Engineering, King's College London, Strand, London ,WC2R 2LS, U.K. (e-mail: hak-keung.lam@kcl.ac.uk).

B. Xiao is with the Hamlyn Centre for Robotic Surgery, Imperial College London, London SW7 2AZ, U.K. (e-mail: b.xiao@imperial.ac.uk).

L.Wu is with the Department of Control Science and Engineering, Harbin Institute of Technology, Harbin 150001, China (e-mail: ligangwu@hit.edu.cn).

categorized as 1) Global boundary information of MFs, 2) Local boundary information of MFs, 3) Approximate MFs that the approximation methods include staircase method, piecewise linear method, polynomial method and Taylor series method [29]. Given that approximate membership function is difficult to perfectly capture all the information of upper and lower bound MFs, and the computational complexity will increase with the increase of approximation degree, how to capture more information of MFs with reasonable computational demand is a point to be explored in this paper. Some notable related practical applications of IT2 fuzzy models in various types of systems are shown in [30]–[34], which will enlighten the theoretical applications studied in this paper. Among them, [30]–[32] explored the implement of IT2 fuzzy model in mobile robots systems. [33] improved the control performance of the generator-based wind turbines by using IT2 fuzzy model. [34] implemented the IT2 fuzzy framework to the control problem of power system.

Considering the uncertainty of MFs of IT2 FMB system and the complexity and instability of the system caused by state delay, for the past few years, the study of delayed IT2 T-S systems has been paid more and more attention. In [35], stability condition analysis and state feedback control synthesis of delayed IT2 FMB systems are carried out. [36] designed an optimal guaranteed cost sliding-mode controller for delayed IT2 T-S fuzzy systems. Some other noteworthy results can be found in [37]–[39]. Nevertheless, to the best of the authors' knowledge, there are few results about the design of dynamic $\ell_2 - \ell_\infty$ output feedback controller for delayed IT2 FMB systems, and the research on it has theoretical significance and practical application prospect through the above discussion. In addition, there are still some aspects that can be further optimized and improved in the analysis of the IT2 FMB systems. Comparing to the problem of type-1 FMB systems, the challenges exist in the analysis of the IT2 MFs and the mismatch between the IT2 controller and the IT2 model. The challenges also exist in how to make more use of the information contained in the IT2 MFs and how to process the state-delay term, which are essential and will be discussed in this paper.

Motivated by the above mentioned, the $\ell_2 - \ell_\infty$ dynamic output controller design of delayed IT2 T-S is studied in this research. First, by constructing the Lyapunov-Krasovskii function, the stability condition of the closed-loop delayed IT2 T-S fuzzy systems is analyzed. The matrices constructed in the condition are intended to avoid unnecessary amplification which increases conservativeness when designing DOF controller. Second, based on the above analysis, an LMI-based method of DOF controller design is proposed. Wirtinger-based inequality [40]–[42], of which Jensen inequality [43] is a corollary, is applied to deal with the time delay term in the delayed IT2 T-S fuzzy systems. Based on cone complement linearization (CCL) and convex linearization process, an effective algorithm with iterative procedure is designed to obtain parameters of the controller. Inspired by [11], [12] and considering the difference between the MFs of IT2 fuzzy systems and type-1 fuzzy systems, a MFD method based on the staircase upper and lower bound of IT2 MFs is designed.

Compared with [44], [45], the method in this paper captures more information in the MFs. The re-designed staircase MFD method in this paper has a good effect on reducing the conservativeness for the analysis for IT2 T-S fuzzy systems. Moreover, the differences between the approximation staircase membership functions and the upper and lower bound membership functions are considered in the parameters to further relax the stability analysis results. Compared with [29], [37], the MFs dependent method is improved for IT2 fuzzy sets to make the approximation upper and lower bound MFs to be flexibly selected in the practical implement.

The rest content of this paper consists of the following parts. Section II introduces the system modeling and the problem studied, as well as some definitions and lemmas needed in the main result section. Section III introduces the main results of this paper and the process of its analysis. Section IV shows the simulation example to verify the effectiveness of the obtained theorems. Section V summarizes the main content of this paper and shows the conclusion.

II. PROBLEM FORMULATION AND PRELIMINARIES

A. IT2 FMB system

In this paper, we express nonlinear systems with uncertainty for the following discrete-time state-delay IT2 T-S FMB system (1) with n_p rules:

Plant Rule i : IF $f_1(\rho(k))$ is $\tilde{W}_1^i$ AND ... AND $f_{n_\alpha}(\rho(k))$ is $\tilde{W}_{n_\alpha}^i$ THEN:

$$\begin{aligned} x(\kappa + 1) &= A_i x(\kappa) + A_{di} x(\kappa - d(\kappa)) + B_{1i} u(\kappa) + D_i \omega(\kappa), \\ y(\kappa) &= C_{yi} x(\kappa) + C_{ydi} x(\kappa), \\ z(\kappa) &= C_i x(\kappa) + C_{di} x(\kappa - d(\kappa)) + B_{2i} u(\kappa), \end{aligned} \quad (1)$$

where $\tilde{W}_\alpha^i$ and $f_\alpha(\rho(\kappa))$ stand for the IT2 fuzzy set and the premise variable; $A_i, A_{di}, B_{1i}, B_{2i}, C_i, C_{yi}, C_{di}, C_{ydi}$, and D_i are the matrices with appropriate dimensions; $x(\kappa) \in \mathbb{R}^{n_x}$, $y(\kappa) \in \mathbb{R}^{n_y}$, $u(\kappa) \in \mathbb{R}^{n_u}$, $\omega(\kappa) \in \mathbb{R}^{n_\omega}$ and $z(\kappa) \in \mathbb{R}^{n_z}$ stand for the system state vector, the measured output, the control input vector, the disturbance input and the controlled output, respectively; $\alpha = 1, 2, \dots, n_\alpha$; $i = 1, 2, \dots, n_p$; n_α is a positive integer; The following shows the firing strength of the i th fuzzy rule represented by interval sets:

$$W_i(\rho(\kappa)) = [\underline{w}_i(\rho(\kappa)), \bar{w}_i(\rho(\kappa))], i = 1, 2, \dots, n_p, \quad (2)$$

where

$$\begin{aligned} \underline{w}_i(\rho(\kappa)) &= \prod_{\alpha=1}^{n_\alpha} \underline{\mu}_{\tilde{W}_\alpha^i}(f_\alpha(\rho(\kappa))) \geq 0 \\ \bar{w}_i(\rho(\kappa)) &= \prod_{\alpha=1}^{n_\alpha} \bar{\mu}_{\tilde{W}_\alpha^i}(f_\alpha(\rho(\kappa))) \geq 0. \end{aligned}$$

$\underline{\mu}_{\tilde{M}_\alpha^i}(f_\alpha(\rho(\kappa))) \geq 0$ and $\bar{\mu}_{\tilde{M}_\alpha^i}(f_\alpha(\rho(\kappa))) \geq 0$ stand for the lower and upper MFs, respectively. $\bar{\mu}_{\tilde{M}_\alpha^i}(f_\alpha(\rho(\kappa))) \geq \underline{\mu}_{\tilde{M}_\alpha^i}(f_\alpha(\rho(\kappa)))$ for all i . $\underline{w}_i(x(\kappa))$ and $\bar{w}_i(x(\kappa))$ stand for the lower and upper grades of membership, respectively.

$\bar{w}_i(\rho(\kappa)) \geq w_i(\rho(\kappa))$ for all i . A compact formulation of system (1) is shown as follows:

$$\begin{aligned} x(\kappa+1) &= \sum_{i=1}^{n_p} \tilde{w}_i(\rho(\kappa)) [A_i x(\kappa) + A_{di} x(\kappa - d(\kappa)) \\ &\quad + B_{1i} u(\kappa) + D_i \omega(\kappa)], \\ y(\kappa) &= \sum_{i=1}^{n_p} \tilde{w}_i(\rho(\kappa)) [C_{yi} x(\kappa) + C_{ydi} x(\kappa - d(\kappa))], \\ z(\kappa) &= \sum_{i=1}^{n_p} \tilde{w}_i(\rho(\kappa)) [C_i x(\kappa) + C_{di} x(\kappa - d(\kappa))] \end{aligned} \quad (3)$$

where

$$\begin{aligned} \tilde{w}_i(x(\kappa)) &= \frac{\underline{a}_i(\rho(\kappa)) \underline{w}_i(\rho(\kappa)) + \bar{a}_i(\rho(\kappa)) \bar{w}_i(\rho(\kappa))}{\sum_{k=1}^{n_p} (\underline{a}_k(\rho(\kappa)) \underline{w}_k(\rho(\kappa)) + \bar{a}_k(\rho(\kappa)) \bar{w}_k(\rho(\kappa)))}, \\ \forall i, \sum_{i=1}^{n_p} \tilde{w}_i(\rho(\kappa)) &= 1. \end{aligned}$$

$\underline{a}_i(\rho(\kappa))$ and $\bar{a}_i(\rho(\kappa))$ are nonlinear functions which satisfy:

- (i) $0 \leq \underline{a}_i(\rho(\kappa)) \leq 1$ and $0 \leq \bar{a}_i(\rho(\kappa)) \leq 1$.
- (ii) $\underline{a}_i(\rho(\kappa)) + \bar{a}_i(\rho(\kappa)) = 1$.

B. IT2 Fuzzy DOF Controller

In this paper, we focus on the IT2 fuzzy DOF controller expressed by the following form.

$$\begin{aligned} \hat{x}(\kappa+1) &= \sum_{i=1}^{n_p} \sum_{j=1}^{n_c} \tilde{w}_i(\rho(\kappa)) \tilde{m}_j(\varrho(\kappa)) [A_{cij} \hat{x}(\kappa) \\ &\quad + B_{cij} y(\kappa)], \\ u(\kappa) &= \sum_{j=1}^{n_c} \tilde{m}_j(\varrho(\kappa)) [C_{cj} \hat{x}(\kappa)], \end{aligned} \quad (4)$$

where $\tilde{M}_\beta^j$ and $g_\beta(\varrho(\kappa))$ stand for the IT2 fuzzy set and the premise variable, respectively. A_{cij} , B_{cij} and C_{cj} stand for the control matrices with appropriate dimensions. $\hat{x}(\kappa) \in \mathbb{R}^{n_x}$ stand for the controller state vector of the DOF controller; $j = 1, 2, \dots, n_c$; $\beta = 1, 2, \dots, n_\beta$; n_β is a positive integer; The following shows the firing strength of the j th fuzzy rule represented by interval sets:

$$M_j(\varrho(\kappa)) = [\underline{m}_j(\varrho(\kappa)), \bar{m}_j(\varrho(\kappa))], j = 1, 2, \dots, n_c \quad (5)$$

where

$$\begin{aligned} \underline{m}_j(\varrho(\kappa)) &= \prod_{\beta=1}^{n_\beta} \underline{\mu}_{\tilde{M}_\beta^j}(g_\beta(\varrho(\kappa))) \geq 0, \\ \bar{m}_j(\varrho(\kappa)) &= \prod_{\beta=1}^{n_\beta} \bar{\mu}_{\tilde{M}_\beta^j}(g_\beta(\varrho(\kappa))) \geq 0, \end{aligned}$$

$\underline{\mu}_{\tilde{M}_\beta^j}(g_\beta(\varrho(\kappa))) \geq 0$ and $\bar{\mu}_{\tilde{M}_\beta^j}(g_\beta(\varrho(\kappa))) \geq 0$ stand for the lower and upper MFs, respectively. $\bar{\mu}_{\tilde{M}_\beta^j}(g_\beta(\varrho(\kappa))) \geq \underline{\mu}_{\tilde{M}_\beta^j}(g_\beta(\varrho(\kappa)))$. $\underline{m}_j(\varrho(\kappa))$ and $\bar{m}_j(\varrho(\kappa))$ stand for the lower

and upper grades of membership, respectively. $\bar{m}_j(\varrho(\kappa)) \geq \underline{m}_j(\varrho(\kappa))$.

$$\begin{aligned} \tilde{m}_j(\varrho(\kappa)) &= \frac{\underline{b}_j(\varrho(\kappa)) \underline{m}_j(\varrho(\kappa)) + \bar{b}_j(\varrho(\kappa)) \bar{m}_j(\varrho(\kappa))}{\sum_{k=1}^{n_c} (\underline{b}_k(\varrho(\kappa)) \underline{m}_k(\varrho(\kappa)) + \bar{b}_k(\varrho(\kappa)) \bar{m}_k(\varrho(\kappa)))} \\ &\geq 0, \forall j \text{ and } \sum_{j=1}^{n_c} \tilde{m}_j(\varrho(\kappa)) = 1. \end{aligned}$$

$\underline{b}_j(\varrho(\kappa))$ and $\bar{b}_j(\varrho(\kappa))$ are users-determined functions which satisfy:

- (i) $0 \leq \underline{b}_j(\varrho(\kappa)) \leq 1$ and $0 \leq \bar{b}_j(\varrho(\kappa)) \leq 1$.
- (ii) $\underline{b}_j(\varrho(\kappa)) + \bar{b}_j(\varrho(\kappa)) = 1$.

C. Augmented Closed-loop System

The augmented system consisting of the IT2 FMB system with state delay and the controller is represented as follows:

$$\begin{aligned} \bar{x}(\kappa+1) &= \sum_{i=1}^{n_p} \sum_{j=1}^{n_c} \tilde{w}_i(\rho(\kappa)) \tilde{m}_j(\varrho(\kappa)) [\bar{A}_{ij} \bar{x}(\kappa) \\ &\quad + \bar{A}_{dij} H \bar{x}(\kappa - d(\kappa)) + \bar{D}_i \omega(\kappa)], \\ z(\kappa) &= \sum_{i=1}^{n_p} \sum_{j=1}^{n_c} \tilde{w}_i(\rho(\kappa)) \tilde{m}_j(\varrho(\kappa)) [\bar{C}_{ij} \bar{x}(\kappa) \\ &\quad + \bar{C}_{dij} \bar{x}(\kappa - d(\kappa))], \end{aligned} \quad (6)$$

where $\bar{x} = [x^T(\kappa), \hat{x}^T(\kappa)]^T$, $H = [I, 0]$,

$$\begin{aligned} \bar{A}_{ij} &= \begin{bmatrix} A_i & B_{1i} C_{cj} \\ B_{cj} C_{yi} & A_{cij} \end{bmatrix}, \bar{A}_{dij} = \begin{bmatrix} A_{di} \\ B_{cj} C_{ydi} \end{bmatrix} \\ \bar{C}_{ij} &= [C_i \quad B_{2i} C_{cj}], \bar{C}_{di} = [C_{di} \quad 0], \\ \bar{D}_i &= \begin{bmatrix} D_i \\ 0 \end{bmatrix}. \end{aligned}$$

From (3) and (4), we can obtain

$$\begin{aligned} \bar{x}(\kappa+1) &= \sum_{i=1}^{n_p} \sum_{j=1}^{n_c} h_{ij}(\iota(\kappa)) [\bar{A}_i \bar{x}(\kappa) + \bar{A}_{di} \bar{x}(\kappa - d(\kappa)) \\ &\quad + \bar{D}_i \omega(\kappa)], \\ z(\kappa) &= \sum_{i=1}^{n_p} \sum_{j=1}^{n_c} h_{ij}(\iota(\kappa)) [\bar{C}_i \bar{x}(\kappa) + \bar{C}_{di} \bar{x}(\kappa - d(\kappa))], \end{aligned} \quad (7)$$

where $h_{ij}(\iota(\kappa)) = \tilde{w}_i(\rho(\kappa)) \tilde{m}_j(\varrho(\kappa))$, $\sum_{i=1}^{n_p} \sum_{j=1}^{n_c} h_{ij}(\iota(\kappa)) = 1$ and $\iota(\kappa) = [\rho^T(\kappa), \varrho^T(\kappa)]^T$.

D. Definitions

Definition 1: The closed-loop state-delay IT2 FMB control system (7) is said to be asymptotically stable under $\omega(\kappa) = 0$ if the following condition satisfies:

$$\lim_{k \rightarrow \infty} |\bar{x}(\kappa)| = 0.$$

For an asymptotically stable closed-loop state-delay IT2 FMB control system (7), we have $z \equiv z(\kappa) \in \ell_2[0, \infty)$ when $\omega \equiv \omega(\kappa) \in \ell_2[0, \infty)$.

Definition 2: [2] The closed-loop state-delay IT2 FMB control system (7) is said to be asymptotically stable with a $\ell_2 - \ell_\infty$ performance $\gamma > 0$ if it is asymptotically stable and under zero initial condition ($\bar{x}(\kappa) = 0, \forall t \leq 0$) for all non-zero $\omega \in \ell_2[0, \infty)$,

$$\sup_{\kappa} \sqrt{z^T(\kappa)z(\kappa)} < \gamma \sqrt{\sum_{k=0}^{\infty} \omega^T(\kappa)\omega(\kappa)}.$$

for all $\omega \in \ell_2[0, \infty)$.

Lemma 1: (Wirtinger inequality) [41], [42] For symmetric matrix $M > 0$ with appropriate dimensions, integers $a < b$, then the inequality blow holds.

$$\begin{aligned} & - (b-a) \sum_{l=\kappa-b}^{\kappa-a-1} \delta^T(l) M \delta(s) \\ & \leq - \begin{bmatrix} \Lambda_0 \\ \Lambda_1 \end{bmatrix}^T \begin{bmatrix} M & 0 \\ 0 & 3M \end{bmatrix} \begin{bmatrix} \Lambda_0 \\ \Lambda_1 \end{bmatrix}, \end{aligned} \quad (8)$$

where

$$\begin{aligned} \delta(\kappa) &= \bar{x}(\kappa+1) - \bar{x}(\kappa), \Lambda_0 = \bar{x}(\kappa-a) - \bar{x}(\kappa-b), \\ \Lambda_1 &= \bar{x}(\kappa-a) + \bar{x}(\kappa-b) - \frac{2}{b-a+1} \left[\sum_{l=\kappa-b}^{\kappa-a} \bar{x}(l) \right]. \end{aligned}$$

III. MAIN RESULTS

Based on the preliminaries above, this section will show the main results of this paper.

Theorem 1: In terms of the closed-loop state-delay IT2 T-S FMB control system in (7), it is asymptotically stable with a $\ell_2 - \ell_\infty$ performance γ if there exist matrices $P, Q, R_1, R_2, \Xi_{ij1}, \Xi_{ij2}, X_{ij1}, X_{ij2}, Y_{ij1}$ and Y_{ij2} satisfying the following inequalities for $i = 1, 2, \dots, n_p; j = 1, 2, \dots, n_c$:

$$\begin{aligned} & \Upsilon_{ij1} + \Xi_{ij1} - \bar{\Xi}_{ij1} + \sum_{s=1}^{n_p} \sum_{t=1}^{n_c} [(\hat{h}_{st}(\hat{k}\sigma_{\hat{k}})(-\bar{\Xi}_{st1}) + \Delta \underline{h}_{stmin}) \\ & \times (-\bar{\Xi}_{st1}) + (\Delta \underline{h}_{stmax} - \Delta \underline{h}_{stmin})X_{ij1} + \hat{h}_{st}(\hat{k}\sigma_{\hat{k}})\bar{\Xi}_{st1} \\ & + \Delta \bar{h}_{stmin}\bar{\Xi}_{st1} + (\Delta \bar{h}_{stmax} - \Delta \bar{h}_{stmin})Y_{ij1}] < 0 \end{aligned} \quad (9)$$

$$\begin{aligned} & \Upsilon_{ij1} + \Xi_{ij2} - \bar{\Xi}_{ij2} + \sum_{s=1}^{n_p} \sum_{t=1}^{n_c} [(\hat{h}_{st}(\hat{k}\sigma_{\hat{k}})(-\bar{\Xi}_{st2}) + \Delta \underline{h}_{stmin}) \\ & \times (-\bar{\Xi}_{st2}) + (\Delta \underline{h}_{stmax} - \Delta \underline{h}_{stmin})X_{ij2} + \hat{h}_{st}(\hat{k}\sigma_{\hat{k}})\bar{\Xi}_{st2} \\ & + \Delta \bar{h}_{stmin}\bar{\Xi}_{st2} + (\Delta \bar{h}_{stmax} - \Delta \bar{h}_{stmin})Y_{ij2}] < 0 \end{aligned} \quad (10)$$

$$-\bar{\Xi}_{st1} - X_{ij1} < 0, \bar{\Xi}_{st1} - Y_{ij1} < 0 \quad (11)$$

$$-\bar{\Xi}_{st2} - X_{ij2} < 0, \bar{\Xi}_{st2} - Y_{ij2} < 0 \quad (12)$$

$$P > 0, Q > 0, R_1 > 0, R_2 > 0, \Xi_{ij1} \geq 0, \Xi_{ij2} \geq 0, \quad (13)$$

$$\bar{\Xi}_{ij1} \geq 0, \bar{\Xi}_{ij2} \geq 0, X_{ij1} \geq 0, X_{ij2} \geq 0, Y_{ij1} \geq 0, Y_{ij2} \geq 0, \quad (14)$$

where $\hat{h}_{ij}(\hat{k}\sigma_{\hat{k}})$ and $\hat{\bar{h}}_{ij}(\hat{k}\sigma_{\hat{k}})$ are the staircase MFs that approximate to the lower and upper MFs $\underline{h}_{ij}$ and $\bar{h}_{ij}$. $\underline{h}_{ij}$ and $\bar{h}_{ij}$ satisfy $\underline{h}_{ij} \leq h_{ij}(\iota(\kappa)) \leq \bar{h}_{ij}$, where $\hat{k}$ and $\sigma_{\hat{k}}$ denote the number and width of the stairs. Denote $\Delta \underline{h}_{ij}(\hat{k}\sigma_{\hat{k}}) = \underline{h}_{ij} - \hat{h}_{ij}(\hat{k}\sigma_{\hat{k}})$ and $\Delta \bar{h}_{ij}(\hat{k}\sigma_{\hat{k}}) = \bar{h}_{ij} - \hat{\bar{h}}_{ij}(\hat{k}\sigma_{\hat{k}})$. Then $\Delta \underline{h}_{ijmin} =$

$$\min(\Delta \underline{h}_{ij}(\hat{k}\sigma_{\hat{k}})), \Delta \underline{h}_{ijmax} = \max(\Delta \underline{h}_{ij}(\hat{k}\sigma_{\hat{k}})), \Delta \bar{h}_{ijmin} = \min(\Delta \bar{h}_{ij}(\hat{k}\sigma_{\hat{k}})) \text{ and } \Delta \bar{h}_{ijmax} = \max(\Delta \bar{h}_{ij}(\hat{k}\sigma_{\hat{k}})).$$

$$\begin{aligned} \Upsilon_1^{11} &= -P + \underline{d}^2 R_1 + \bar{d}^2 R_2 \\ \Upsilon_{ij1}^{12} &= P \bar{A}_{ij} - \underline{d}^2 R_1 - \bar{d}^2 R_2 \\ \Upsilon_1^{22} &= -P + (\bar{d} - \underline{d} + 1)H^T Q H + \underline{d}^2 R_1 + \bar{d}^2 R_2 \\ &\quad - 4R_1 - 4R_2 \\ \Omega_{ij2} &= \begin{bmatrix} \bar{C}_{ij}^T \bar{C}_{ij} - \frac{1}{2}\gamma^2 P & \bar{C}_{ij}^T \bar{C}_{di} \\ * & \bar{C}_{di}^T \bar{C}_{di} - \frac{1}{2}\gamma^2 P \end{bmatrix} \end{aligned}$$

Proof 1: First, choose a Lyapunov functional candidate as

$$\begin{aligned} V(\kappa) &= V_1(\kappa) + V_2(\kappa) + V_3(\kappa) + V_4(\kappa). \\ V_1(\kappa) &= \bar{x}^T(\kappa) P \bar{x}(\kappa), \\ V_2(\kappa) &= \sum_{g=-\underline{d}+1}^{-\underline{d}+1} \sum_{l=\kappa-1+g}^{\kappa-1} \bar{x}^T(l) H^T Q H \bar{x}(l), \\ V_3(\kappa) &= \underline{d} \sum_{g=-\underline{d}}^{-1} \sum_{l=\kappa+g}^{\kappa-1} \delta^T(l) R_1 \delta(l) \\ &\quad + \bar{d} \sum_{g=-\bar{d}}^{-1} \sum_{l=\kappa+g}^{\kappa-1} \delta^T(l) R_2 \delta(l), \end{aligned}$$

where $\delta(\kappa) = \bar{x}(\kappa+1) - \bar{x}(\kappa)$,

Then calculate the difference of $V_1(\kappa)$, $V_2(\kappa)$ and $V_3(\kappa)$:

$$\begin{aligned} \Delta V_1(\kappa) &= \bar{x}^T(\kappa+1) P \bar{x}(\kappa+1) - \bar{x}^T(\kappa) P \bar{x}(\kappa) \\ \Delta V_2(\kappa) &\leq \sum_{i=1}^{n_p} \sum_{j=1}^{n_c} h_{ij}(\bar{x}(\kappa)) \\ &\quad \times [(\bar{d} - \underline{d} + 1) \bar{x}^T(\kappa) H^T Q H \bar{x}(\kappa) \\ &\quad - \bar{x}^T(\kappa - d(\kappa)) H^T Q H \bar{x}(\kappa - d(\kappa))] \\ &= \sum_{i=1}^{n_p} \sum_{j=1}^{n_c} h_{ij}(\bar{x}(\kappa)) \\ &\quad \times [(\bar{d} - \underline{d} + 1) \bar{x}^T(\kappa) H^T Q H \bar{x}(\kappa) \\ &\quad - \bar{x}^T(\kappa - d(\kappa)) Q \bar{x}(\kappa - d(\kappa))] \end{aligned}$$

Using discrete Wirtinger-based inequality in Lemma 1, we have

$$\begin{aligned} \Delta V_3(\kappa) &= \underline{d}^2 \delta^T(\kappa) R_1 \delta(\kappa) - \underline{d} \sum_{l=\kappa-\underline{d}}^{\kappa-1} \delta^T(l) R_1 \delta(l) \\ &\quad + \bar{d}^2 \delta^T(\kappa) R_2 \delta(\kappa) - \bar{d} \sum_{l=\kappa-\bar{d}}^{\kappa-1} \delta^T(l) R_2 \delta(l), \\ &\leq \underline{d}^2 \delta^T(\kappa) R_1 \delta(\kappa) - \varsigma_1^T(\kappa) \Gamma_1 \varsigma_1(\kappa) \\ &\quad + \bar{d}^2 \delta^T(\kappa) R_2 \delta(\kappa) - \varsigma_2^T(\kappa) \Gamma_2 \varsigma_2(\kappa) \end{aligned}$$

$$\Upsilon_{ij1} = \begin{bmatrix} \Upsilon_1^{11} & \Upsilon_{ij1}^{12} & P\bar{A}_{dij} & 0 & 0 & 0 & 0 & P\bar{D}_i \\ * & \Upsilon_1^{22} & 0 & -2R_1 & -2R_2 & 6R_1 & 6R_2 & 0 \\ * & * & -Q & 0 & 0 & 0 & 0 & 0 \\ * & * & * & -4R_1 & 0 & 6R_1 & 0 & 0 \\ * & * & * & * & -4R_2 & 0 & 6R_2 & 0 \\ * & * & * & * & * & -12R_1 & 0 & 0 \\ * & * & * & * & * & * & -12R_2 & 0 \\ * & * & * & * & * & * & * & -I \end{bmatrix},$$

where

$$\begin{aligned} \varsigma_1(\kappa) &= \begin{bmatrix} \bar{x}^T(\kappa) & \bar{x}^T(\kappa - \underline{d}) & \frac{1}{\underline{d}+1} \sum_{l=\kappa-\underline{d}}^k \bar{x}(l) \end{bmatrix}^T \\ \varsigma_2(\kappa) &= \begin{bmatrix} \bar{x}^T(\kappa) & \bar{x}^T(\kappa - \bar{d}) & \frac{1}{\bar{d}+1} \sum_{l=\kappa-\bar{d}}^k \bar{x}(l) \end{bmatrix}^T \\ \Gamma_1 &= \begin{bmatrix} 4R_1 & 2R_1 & -6R_1 \\ * & 4R_1 & -6R_1 \\ * & * & 12R_1 \end{bmatrix} \\ \Gamma_2 &= \begin{bmatrix} 4R_2 & 2R_2 & -6R_2 \\ * & 4R_2 & -6R_2 \\ * & * & 12R_2 \end{bmatrix} \end{aligned}$$

Notice that

$$\begin{aligned} 0 &= -2\bar{x}(\kappa+1)P \left\{ \bar{x}(\kappa+1) - \sum_{i=1}^{n_p} \sum_{j=1}^{n_c} h_{ij}(\iota(\kappa)) \right. \\ &\quad \times [\bar{A}_{ij}\bar{x}(\kappa) + \bar{A}_{dij}H\bar{x}(\kappa - d(\kappa)) + \bar{D}_i\omega(\kappa)] \Big\} \end{aligned}$$

Then we have

$$\begin{aligned} &\Delta V(\kappa) - \omega^T(\kappa)\omega(\kappa) \\ &\leq \sum_{i=1}^{n_p} \sum_{j=1}^{n_c} h_{ij}\xi^T(\kappa) \left\{ \Upsilon_{ij1} + \Xi_{ij1} - \Xi_{ij1} + \sum_{s=1}^{n_p} \sum_{t=1}^{n_c} [\underline{h}_{st} \right. \\ &\quad \times (-\Xi_{st1}) + \bar{h}_{st}\Xi_{st1}] \Big\} \xi(\kappa) \\ &= \sum_{i=1}^{n_p} \sum_{j=1}^{n_c} h_{ij}\xi^T(\kappa) \left\{ \Upsilon_{ij1} + \Xi_{ij1} - \Xi_{ij1} + \sum_{s=1}^{n_p} \sum_{t=1}^{n_c} [\hat{h}_{st}(\hat{k}\sigma_{\hat{k}}) \right. \\ &\quad \times (-\Xi_{st1}) + \Delta \underline{h}_{st}(-\Xi_{st1}) + \hat{h}_{st}(\hat{k}\sigma_{\hat{k}})\Xi_{st1} + \Delta \bar{h}_{st}\Xi_{st1}] \Big\} \xi(\kappa) \\ &= \sum_{i=1}^{n_p} \sum_{j=1}^{n_c} h_{ij}\xi^T(\kappa) \left\{ \Upsilon_{ij1} + \Xi_{ij1} - \Xi_{ij1} + \sum_{s=1}^{n_p} \sum_{t=1}^{n_c} [\hat{h}_{st}(\hat{k}\sigma_{\hat{k}}) \right. \\ &\quad \times (-\Xi_{st1}) + (\Delta \underline{h}_{st} - \Delta \underline{h}_{stmin} + \Delta \underline{h}_{stmin})(-\Xi_{st1}) \\ &\quad + \hat{h}_{st}(\hat{k}\sigma_{\hat{k}})\Xi_{st1} + (\Delta \bar{h}_{st} - \Delta \bar{h}_{stmin} + \Delta \bar{h}_{stmin})\Xi_{st1}] \Big\} \xi(\kappa) \\ &= \sum_{i=1}^{n_p} \sum_{j=1}^{n_c} h_{ij}\xi^T(\kappa) \left\{ \Upsilon_{ij1} + \Xi_{ij1} - \Xi_{ij1} + \sum_{s=1}^{n_p} \sum_{t=1}^{n_c} [\hat{h}_{st}(\hat{k}\sigma_{\hat{k}}) \right. \\ &\quad \times (-\Xi_{st1}) + (\Delta \underline{h}_{st} - \Delta \underline{h}_{stmin})(-\Xi_{st1} + X_{ij1} - X_{ij1}) \\ &\quad + \Delta \underline{h}_{stmin}(-\Xi_{st1}) + \hat{h}_{st}(\hat{k}\sigma_{\hat{k}})\Xi_{st1} + (\Delta \bar{h}_{st} - \Delta \bar{h}_{stmin})(\Xi_{st1} \\ &\quad + Y_{ij1} - Y_{ij1}) + \Delta \bar{h}_{stmin}\Xi_{st1}] \Big\} \xi(\kappa) \\ &\leq \sum_{i=1}^{n_p} \sum_{j=1}^{n_c} h_{ij}\xi^T(\kappa) \left\{ \Upsilon_{ij1} + \Xi_{ij1} - \Xi_{ij1} + \sum_{s=1}^{n_p} \sum_{t=1}^{n_c} [(\hat{h}_{st}(\hat{k}\sigma_{\hat{k}}) \right. \\ &\quad \times (-\Xi_{st1}) + (\Delta \underline{h}_{st} - \Delta \underline{h}_{stmin})(-\Xi_{st1} - X_{ij1}) \\ &\quad + \Delta \underline{h}_{stmin}(-\Xi_{st1}) + (\Delta \underline{h}_{stmax} - \Delta \underline{h}_{stmin})X_{ij1} \\ &\quad + \hat{h}_{st}(\hat{k}\sigma_{\hat{k}})\Xi_{st1} + (\Delta \bar{h}_{st} - \Delta \bar{h}_{stmin})(\Xi_{st1} - Y_{ij1}) \\ &\quad + \Delta \bar{h}_{stmin}\Xi_{st1} + (\Delta \bar{h}_{stmax} - \Delta \bar{h}_{stmin})Y_{ij1}] \Big\} \xi(\kappa) \end{aligned}$$

where $\xi(\kappa) = [\bar{x}^T(\kappa+1), \bar{x}^T(\kappa), \bar{x}^T(\kappa - d(\kappa)), \bar{x}^T(\kappa - \underline{d}), \bar{x}^T(\kappa - \bar{d}), \frac{1}{\underline{d}+1} \sum_{l=\kappa-\underline{d}}^k \bar{x}(l), \frac{1}{\bar{d}+1} \sum_{l=\kappa-\bar{d}}^k \bar{x}(l)]^T$. (9) and (11) indicate

$$\Delta V(\bar{x}(\kappa)) < \omega^T(\kappa)\omega(\kappa). \quad (15)$$

Taking sum from 0 to $T-1$ of the both sides of (15), we obtain

$$V(T) - V(0) = \sum_{k=0}^{T-1} \Delta V(\kappa) < \sum_{k=0}^{T-1} \omega^T(\kappa)\omega(\kappa). \quad (16)$$

Noticing $V(0) = 0$ (zero initial condition), then following inequality is obtained.

$$V(T) < \sum_{k=0}^{T-1} \omega^T(\kappa) \omega(\kappa) \quad (17)$$

Considering zero initial condition and (17), we obtain

$$\bar{x}^T(\kappa) P \bar{x}(\kappa) < V(\kappa) < \sum_{k=0}^{\infty} \omega^T(\kappa) \omega(\kappa), \quad (18)$$

$$\bar{x}^T(\kappa - d(\kappa)) P \bar{x}(\kappa - d(\kappa)) < \sum_{k=0}^{\infty} \omega^T(\kappa) \omega(\kappa). \quad (19)$$

Next, similar to above process, we consider

$$\begin{aligned} & z^T(\kappa) z(\kappa) - \frac{1}{2} \gamma^2 \bar{x}^T(\kappa) P \bar{x}(\kappa) \\ & - \frac{1}{2} \gamma^2 \bar{x}^T(\kappa - d(\kappa)) P \bar{x}(\kappa - d(\kappa)) \\ & \leq \sum_{i=1}^{n_p} \sum_{j=1}^{n_c} h_{ij}(\bar{x}(\kappa)) [\bar{C}_{ij} \bar{x}(\kappa) + \bar{C}_{ijd} \bar{x}(\kappa - d(\kappa))]^T \\ & \quad \times [\bar{C}_{ij} \bar{x}(\kappa) + \bar{C}_{ijd} \bar{x}(\kappa - d(\kappa))] - \frac{1}{2} \gamma^2 \bar{x}^T(\kappa) P \bar{x}(\kappa) \\ & \quad - \frac{1}{2} \gamma^2 \bar{x}^T(\kappa - d(\kappa)) P \bar{x}(\kappa - d(\kappa)) \\ & \leq \sum_{i=1}^{n_p} \sum_{j=1}^{n_c} h_{ij} \xi^T(\kappa) \left\{ \Upsilon_{ij2} + \Xi_{ij2} - \bar{\Xi}_{ij2} + \sum_{s=1}^{n_p} \sum_{t=1}^{n_c} [(\hat{h}_{st}(\hat{k}\sigma_{\hat{k}}) \right. \\ & \quad \times (-\bar{\Xi}_{st2}) + (\Delta \bar{h}_{st} - \Delta \bar{h}_{stmin})(-\bar{\Xi}_{st2} - X_{ij2}) \\ & \quad + \Delta \bar{h}_{stmin}(-\bar{\Xi}_{st2}) + (\Delta \bar{h}_{stmax} - \Delta \bar{h}_{stmin}) X_{ij2} \\ & \quad + \hat{h}_{st}(\hat{k}\sigma_{\hat{k}}) \bar{\Xi}_{st2} + (\Delta \bar{h}_{st} - \Delta \bar{h}_{stmin})(\bar{\Xi}_{st2} - Y_{ij2}) \\ & \quad \left. + \Delta \bar{h}_{stmin} \bar{\Xi}_{st2} + (\Delta \bar{h}_{stmax} - \Delta \bar{h}_{stmin}) Y_{ij2}] \right\} \xi(\kappa) \end{aligned}$$

where

$$\mu(\kappa) = \begin{bmatrix} \bar{x}^T(\kappa) & \bar{x}^T(\kappa - d(\kappa)) \end{bmatrix}^T. \quad (20)$$

Then, we have

$$\begin{aligned} & z^T(\kappa) z(\kappa) < \frac{1}{2} \gamma^2 \begin{bmatrix} \bar{x}(\kappa) \\ \bar{x}(\kappa - d(\kappa)) \end{bmatrix}^T \begin{bmatrix} P & 0 \\ * & P \end{bmatrix} \\ & \quad \times \begin{bmatrix} \bar{x}(\kappa) \\ \bar{x}(\kappa - d(\kappa)) \end{bmatrix} < \gamma^2 \sum_{k=0}^{\infty} \omega^T(\kappa) \omega(\kappa). \end{aligned}$$

Taking the supremum of $\sqrt{z^T(\kappa) z(\kappa)}$, then we have

$$\sup_k \sqrt{z^T(\kappa) z(\kappa)} < \gamma \sqrt{\sum_{k=0}^{\infty} \omega^T(\kappa) \omega(\kappa)}.$$

The proof is completed.

Theorem 2: In terms of the state-delay IT2 T-S FMB control system (3), it is asymptotically stable with a $\ell_2 - \ell_\infty$ performance γ if there exist matrices $\mathcal{P}$, $\mathcal{L}$, $\mathcal{G}$, $\mathcal{J}$, $\mathcal{A}_{ij}$, $\mathcal{B}_j$,

$\mathcal{C}_j$, $\hat{Q}^g$, $\hat{R}_1^g$, $\hat{R}_2^g$, $\hat{X}_{ij1}$, $\hat{X}_{ij2}$, $\hat{Y}_{ij1}$, $\hat{Y}_{ij2}$ with $i = 1, 2, \dots, r$, $j = 1, 2, \dots, q$, $g = 1, 2, 3$, satisfying

$$\begin{aligned} & \tilde{\Upsilon}_{ij1} + \tilde{\Xi}_{ij1} - \bar{\Xi}_{ij1} + \sum_{s=1}^{n_p} \sum_{t=1}^{n_c} [(\hat{h}_{st}(\hat{k}\sigma_{\hat{k}})(-\bar{\Xi}_{st1}) + \Delta \bar{h}_{stmin} \\ & \quad \times (-\bar{\Xi}_{st1}) + (\Delta \bar{h}_{stmax} - \Delta \bar{h}_{stmin}) \tilde{X}_{ij1} + \hat{h}_{st}(\hat{k}\sigma_{\hat{k}}) \bar{\Xi}_{st1} \\ & \quad + \Delta \bar{h}_{stmin} \bar{\Xi}_{st1} + (\Delta \bar{h}_{stmax} - \Delta \bar{h}_{stmin}) \tilde{Y}_{ij1}] < 0 \end{aligned} \quad (21)$$

$$\begin{aligned} & \tilde{\Upsilon}_{ij1} + \tilde{\Xi}_{ij2} - \bar{\Xi}_{ij2} + \sum_{s=1}^{n_p} \sum_{t=1}^{n_c} [(\hat{h}_{st}(\hat{k}\sigma_{\hat{k}})(-\bar{\Xi}_{st2}) + \Delta \bar{h}_{stmin} \\ & \quad \times (-\bar{\Xi}_{st2}) + (\Delta \bar{h}_{stmax} - \Delta \bar{h}_{stmin}) \tilde{X}_{ij2} + \hat{h}_{st}(\hat{k}\sigma_{\hat{k}}) \bar{\Xi}_{st2} \\ & \quad + \Delta \bar{h}_{stmin} \bar{\Xi}_{st2} + (\Delta \bar{h}_{stmax} - \Delta \bar{h}_{stmin}) \tilde{Y}_{ij2}] < 0 \end{aligned} \quad (22)$$

$$-\bar{\Xi}_{st1} - \tilde{X}_{ij1} < 0, \bar{\Xi}_{st1} - \tilde{Y}_{ij1} < 0 \quad (23)$$

$$-\bar{\Xi}_{st2} - \tilde{X}_{ij2} < 0, \bar{\Xi}_{st2} - \tilde{Y}_{ij2} < 0 \quad (24)$$

$$\mathcal{P} > 0, \mathcal{L} > 0, \hat{R}_1 > 0, \hat{R}_2 > 0, \bar{\Xi}_{ij1} \geq 0, \bar{\Xi}_{ij2} \geq 0,$$

$$\bar{\Xi}_{ij2} \geq 0, \bar{\Xi}_{ij1} \geq 0, Q > 0, \mathcal{Q} > 0, \quad (25)$$

$$\begin{bmatrix} \mathcal{P} & I \\ * & \mathcal{L} \end{bmatrix} > 0, \quad (26)$$

$$Q\mathcal{Q} = I, \quad (27)$$

where

$$\tilde{\Upsilon}_1^{11} = - \begin{bmatrix} \mathcal{P} & I \\ * & \mathcal{L} \end{bmatrix} + \underline{d}^2 \begin{bmatrix} \tilde{R}_1^1 & \tilde{R}_1^2 \\ * & \tilde{R}_1^3 \end{bmatrix} + \bar{d}^2 \begin{bmatrix} \tilde{R}_2^1 & \tilde{R}_2^2 \\ * & \tilde{R}_2^3 \end{bmatrix},$$

$$\begin{aligned} \tilde{\Upsilon}_{ij1}^{12} &= \begin{bmatrix} \mathcal{P} A_i + \mathcal{B}_j C_{yi} & \mathcal{A}_{ij} \\ A_i \mathcal{L} + B_{1i} C_j \end{bmatrix} - \underline{d}^2 \begin{bmatrix} \tilde{R}_1^1 & \tilde{R}_1^2 \\ * & \tilde{R}_1^3 \end{bmatrix} \\ & - \bar{d}^2 \begin{bmatrix} \tilde{R}_2^1 & \tilde{R}_2^2 \\ * & \tilde{R}_2^3 \end{bmatrix}, \tilde{\Upsilon}_{ij1}^{13} = \begin{bmatrix} \mathcal{P} A_{di} + \mathcal{B}_j C_{ydi} \\ A_{di} \end{bmatrix}, \end{aligned}$$

$$\begin{aligned} \tilde{\Upsilon}_{i1}^{18} &= \begin{bmatrix} \mathcal{P} D_i \\ D_i \end{bmatrix}, \tilde{\Upsilon}_1^{22} = - \begin{bmatrix} \mathcal{P} & I \\ * & \mathcal{L} \end{bmatrix} + \underline{d}^2 \begin{bmatrix} \tilde{R}_1^1 & \tilde{R}_1^2 \\ * & \tilde{R}_1^3 \end{bmatrix} \\ & + \bar{d}^2 \begin{bmatrix} \tilde{R}_2^1 & \tilde{R}_2^2 \\ * & \tilde{R}_2^3 \end{bmatrix} - 4 \begin{bmatrix} \tilde{R}_1^1 & \tilde{R}_1^2 \\ * & \tilde{R}_1^3 \end{bmatrix} - 4 \begin{bmatrix} \tilde{R}_2^1 & \tilde{R}_2^2 \\ * & \tilde{R}_2^3 \end{bmatrix} \end{aligned}$$

$$\tilde{\Upsilon}_{ij1}^{29} = \sqrt{\bar{d} - \underline{d} + 1} \begin{bmatrix} I \\ \mathcal{L} \end{bmatrix},$$

$$\tilde{R}_1 = \begin{bmatrix} \tilde{R}_1^1 & \tilde{R}_1^2 \\ * & \tilde{R}_1^3 \end{bmatrix}, \tilde{R}_2 = \begin{bmatrix} \tilde{R}_2^1 & \tilde{R}_2^2 \\ * & \tilde{R}_2^3 \end{bmatrix},$$

$$\tilde{\Upsilon}_{ij2} = \begin{bmatrix} -\frac{1}{2} \gamma^2 I & \tilde{\Upsilon}_{ij2}^{12} & \tilde{\Upsilon}_{ij2}^{13} \\ * & \tilde{\Upsilon}_2^{22} & 0 \\ * & * & \tilde{\Upsilon}_2^{33} \end{bmatrix},$$

$$\tilde{\Upsilon}_{ij2}^{12} = \begin{bmatrix} C_i & C_i \mathcal{L} + B_{2i} C_j \end{bmatrix}, \tilde{\Upsilon}_{i2}^{13} = \begin{bmatrix} C_{di} & C_{di} \mathcal{L} \end{bmatrix},$$

$$\tilde{\Upsilon}_2^{22} = - \begin{bmatrix} \mathcal{P} & I \\ * & \mathcal{L} \end{bmatrix}, \tilde{\Upsilon}_2^{33} = - \begin{bmatrix} \mathcal{P} & I \\ * & \mathcal{L} \end{bmatrix},$$

Then the $\ell_2 - \ell_\infty$ DOF controller (4) are given by

$$A_{cj} = \mathcal{G}^{-1}(\mathcal{A}_{ij} - \mathcal{P} A_i \mathcal{L} - \mathcal{G} B_{cj} C_{yi} \mathcal{L} - \mathcal{P} B_{1i} C_{cj} \mathcal{J}^T) \mathcal{J}^{-T}, \quad (28)$$

$$B_{cj} = \mathcal{G}^{-1} \mathcal{B}_j, \quad (29)$$

$$C_{cj} = C_j \mathcal{J}^{-T}, \quad (30)$$

where $\mathcal{G}$ and $\mathcal{J}$ are any nonsingular matrices satisfying

$$\mathcal{G} \mathcal{J}^T = I - \mathcal{P} \mathcal{L}. \quad (31)$$

$$\Upsilon_{ij1} = \begin{bmatrix} \tilde{\Upsilon}_1^{11} & \tilde{\Upsilon}_{ij1}^{12} & \tilde{\Upsilon}_{ij1}^{13} & 0 & 0 & 0 & 0 & \tilde{\Upsilon}_{ij1}^{18} & 0 \\ * & \tilde{\Upsilon}_1^{22} & 0 & -2\tilde{R}_1 & -2\tilde{R}_2 & 6\tilde{R}_1 & 6\tilde{R}_2 & 0 & \tilde{\Upsilon}_{ij1}^{29} \\ * & * & -Q & 0 & 0 & 0 & 0 & 0 & 0 \\ * & * & * & -4\tilde{R}_1 & 0 & 6\tilde{R}_1 & 0 & 0 & 0 \\ * & * & * & * & -4\tilde{R}_2 & 0 & 6\tilde{R}_2 & 0 & 0 \\ * & * & * & * & * & -12\tilde{R}_1 & 0 & 0 & 0 \\ * & * & * & * & * & * & -12\tilde{R}_2 & 0 & 0 \\ * & * & * & * & * & * & * & -I & 0 \\ * & * & * & * & * & * & * & * & -\mathcal{Q} \end{bmatrix},$$

Proof 2: Denote $P^{-1} = L$. Then re-write P and L as partitioned matrices:

$$P \triangleq \begin{bmatrix} P_1 & P_2 \\ * & P_3 \end{bmatrix}, L \triangleq \begin{bmatrix} L_1 & L_2 \\ * & L_3 \end{bmatrix}. \quad (32)$$

Define the following nonsingular matrices:

$$K_1 \triangleq \begin{bmatrix} P_1 & I \\ P_2^T & 0 \end{bmatrix}, K_2 \triangleq \begin{bmatrix} I & L_1 \\ 0 & L_2^T \end{bmatrix}. \quad (33)$$

(26) implies that $I - \mathcal{P}\mathcal{L}$ is not singular. Then there exist $\mathcal{G}$ and $\mathcal{L}$ that (31) is satisfied. It is obtained that $PK_2 = K_1$, $LK_1 = K_2$. Define

$$\begin{aligned} P_1 &\triangleq \mathcal{P}, P_2 \triangleq \mathcal{G}, L_1 \triangleq \mathcal{L}, L_2 \triangleq \mathcal{J}, \\ \mathcal{A}_{ij} &\triangleq \mathcal{P}\mathcal{A}_i\mathcal{L} + \mathcal{G}\mathcal{B}_{cj}\mathcal{C}_{ji}\mathcal{L} + \mathcal{P}\mathcal{B}_{1i}\mathcal{C}_{cj}\mathcal{J}^T + \mathcal{G}\mathcal{A}_{cij}\mathcal{J}^T, \\ \mathcal{B}_j &\triangleq \mathcal{G}\mathcal{B}_{cj}, \mathcal{C}_j \triangleq \mathcal{C}_{cj}\mathcal{J}^T. \end{aligned}$$

Perform Schur complement and congruence transformations to (21)-(24) by $\text{diag}\{K_2^{-1}, K_2^{-1}, I, K_2^{-1}, K_2^{-1}, K_2^{-1}, K_2^{-1}, I, I\}$, $\text{diag}\{I, K_2^{-1}, K_2^{-1}\}$, $\text{diag}\{K_2^{-1}, K_2^{-1}, I, K_2^{-1}, K_2^{-1}, I, I\}$ and $\text{diag}\{I, K_2^{-1}, K_2^{-1}\}$, respectively, we can get (9)-(12). This completes the proof.

Notice that due to $Q\mathcal{Q} = I$, some conditions in Theorem 2 are not convex. For solving this, the following CCL process is introduced.

Algorithm 1:

- 1) Set α and approximation MFs. Get a feasible set $(\mathcal{P}^0, \mathcal{L}^0, \tilde{X}_{ij1}^0, \tilde{X}_{ij2}^0, \tilde{Y}_{ij1}^0, \tilde{Y}_{ij2}^0, Q^0, \mathcal{Q}^0, \tilde{R}_1^0, \tilde{R}_2^0, \mathcal{A}_{ij}^0, \mathcal{B}_j^0, \mathcal{C}_j^0, \tilde{\Xi}_{ij1}^0, \tilde{\Xi}_{ij2}^0, \tilde{\Xi}_{ij1}^0, \tilde{\Xi}_{ij2}^0)$ satisfying (21) to (26) and (34). Set the counter $\mathcal{N} = 0$.

$$\begin{bmatrix} Q^{\mathcal{N}} & I \\ I & \mathcal{Q}^{\mathcal{N}} \end{bmatrix} \geq 0. \quad (34)$$

- 2) Solve the following minimization problem

$$\min \text{tr}(Q\mathcal{Q}^{\mathcal{N}} + Q^{\mathcal{N}}\mathcal{Q})$$

subject to (21) to (26) and (34).

- 3) Replace the calculated matrices $(\mathcal{P}, \mathcal{L}, \tilde{X}_{ij1}, \tilde{X}_{ij2}, \tilde{Y}_{ij1}, \tilde{Y}_{ij2}, Q, \mathcal{Q}, \tilde{R}_1^g, \tilde{R}_2^g, \mathcal{A}_{ij}, \mathcal{B}_j, \mathcal{C}_j, \tilde{\Xi}_{ij1}, \tilde{\Xi}_{ij2}, \tilde{\Xi}_{ij1}, \tilde{\Xi}_{ij2})$ into (21). If conditions (21) is satisfied and for a sufficiently enough $\delta > 0$:

$$|\text{tr}(Q\mathcal{Q}^{\mathcal{N}} + Q^{\mathcal{N}}\mathcal{Q}) - 2n| < \delta, \quad (35)$$

Thus the feasible solutions are found. EXIT.

- 4) If $\mathcal{N} > \mathcal{M}$ where $\mathcal{M}$ is the pre-chosen maximum value of iterations by users, EXIT.

- 5) Make $(\mathcal{P}^{\mathcal{N}}, \mathcal{L}^{\mathcal{N}}, \tilde{X}_{ij1}^{\mathcal{N}}, \tilde{X}_{ij2}^{\mathcal{N}}, \tilde{Y}_{ij1}^{\mathcal{N}}, \tilde{Y}_{ij2}^{\mathcal{N}}, Q^{\mathcal{N}}, \mathcal{Q}^{\mathcal{N}}, \tilde{R}_1^{g\mathcal{N}}, \tilde{R}_2^{g\mathcal{N}}, \mathcal{A}_{ij}^{\mathcal{N}}, \mathcal{B}_j^{\mathcal{N}}, \mathcal{C}_j^{\mathcal{N}}, \tilde{\Xi}_{ij1}^{\mathcal{N}}, \tilde{\Xi}_{ij2}^{\mathcal{N}}, \tilde{\Xi}_{ij1}^{\mathcal{N}}, \tilde{\Xi}_{ij2}^{\mathcal{N}})$ equal to $(\mathcal{P}, \mathcal{L}, \tilde{X}_{ij1}, \tilde{X}_{ij2}, \tilde{Y}_{ij1}, \tilde{Y}_{ij2}, Q, \mathcal{Q}, \tilde{R}_1^g, \tilde{R}_2^g, \mathcal{A}_{ij}, \mathcal{B}_j, \mathcal{C}_j, \tilde{\Xi}_{ij1}, \tilde{\Xi}_{ij2}, \tilde{\Xi}_{ij1}, \tilde{\Xi}_{ij2})$, $\mathcal{N} = \mathcal{N} + 1$, and back to Step 2.

IV. SIMULATION EXAMPLE

This section will show a simulation example to verify the effectiveness of the obtained theorems. Consider the following state-delay IT2 T-S FMB control system in the form of (3):

$$\begin{aligned} A_1 &= \begin{bmatrix} 1 & 0.3 \\ 0.4 & 0.5 \end{bmatrix}, A_{d1} = \begin{bmatrix} 0.1 & 0 \\ 0 & 0.1 \end{bmatrix}, B_1 = \begin{bmatrix} 1 \\ 0.5 \end{bmatrix}, \\ C_{y1} &= [1 \quad 0.2], C_{yd1} = [0.05 \quad 0.05], D_1 = \begin{bmatrix} 0.1 \\ 0.5 \end{bmatrix}, \\ C_1 &= [1 \quad 0.2], C_{d1} = [0.01 \quad 0.01], B_{21} = 0.2, \\ A_2 &= \begin{bmatrix} 0.4 & 0.2 \\ 0.2 & 1 \end{bmatrix}, A_{d2} = \begin{bmatrix} 0.1 & 0 \\ 0 & 0.1 \end{bmatrix}, B_{12} = \begin{bmatrix} 0.2 \\ 0.2 \end{bmatrix}, \\ C_{y2} &= [0.3 \quad 0.1], C_{yd2} = [0.03 \quad 0.03], D_2 = \begin{bmatrix} 0.2 \\ 0.1 \end{bmatrix}, \\ C_2 &= [0.7 \quad 0.4], C_{d2} = [0.01 \quad 0.1], B_{22} = 0.2. \end{aligned}$$

The MFs of (3) are shown in the Table I with $\kappa \in [0.15, 0.3]$, $\lambda \in [0, 0.05]$. $\underline{d} = 3$, $\bar{d} = 4$. The related lower and upper MFs are demonstrated in Table II.

TABLE I
THE IT2 MFs OF SYSTEM (3)

The IT2 MFs	
$\tilde{w}_1(x_1) = \begin{cases} \kappa & x_1 \leq -2 \\ -0.5(\kappa - \lambda)(x_1 + \lambda) & -2 < x_1 \leq 0 \\ 0.5(\kappa - \lambda)(x_1 + \lambda) & 0 < x_1 \leq 2 \\ \kappa & 2 < x_1 \end{cases}$	
$\tilde{w}_2(x_1) = 1 - \tilde{w}_1(x_1)$	

Choose the initial state $x_1(0) = -1$, $x_2(0) = -3$ and give the disturbance input:

$$\omega(\kappa) = \begin{cases} 2e^{-0.1k} & 0 < k \leq 40 \\ 0 & k > 40 \end{cases}$$

The open-loop state responses and the output signal of system (3) is shown graphically in Fig. 1, which shows that

TABLE II
THE LOWER AND UPPER MFs OF SYSTEM(3)

The lower MFs	
$\underline{w}_1(x_1) = \begin{cases} 0.15 & x_1 \leq -2 \\ -0.075x_1 & -2 < x_1 \leq 0 \\ 0.075x_1 & 0 < x_1 \leq 2 \\ 0 & 2 < x_1 \end{cases}$	
$\underline{w}_2(x_1) = 1 - \underline{w}_1(x_1)$	
The upper MFs	
$\bar{w}_1(x_1) = \begin{cases} 0.3 & x_1 \leq -2 \\ -0.125x_1 + 0.05 & -2 < x_1 \leq 0 \\ 0.125x_1 + 0.05 & 0 < x_1 \leq 2 \\ 0.05 & 2 < x_1 \end{cases}$	
$\bar{w}_2(x_1) = 1 - \bar{w}_1(x_1)$

Fig. 1. Open-loop state and output signals of system (3).

the system is open-loop unstable. Then, our goal is to design a DOF controller in the form of (4) for the system (3). The IT2 MFs of the controller are shown in Table. III.

TABLE III
THE LOWER AND UPPER MFs OF SYSTEM(4)

The lower MFs	
$\underline{m}_1(x_1) = 0.95 - 0.95e^{-\frac{x_1^2}{2}}$	$\underline{m}_2(x_1) = 1 - \bar{m}_1(x_1)$
The upper MFs	
$\bar{m}_1(x_1) = 1 - 0.95e^{-\frac{x_1^2}{0.7}}$	$\bar{m}_2(x_1) = 1 - \underline{m}_1(x_1)$

Then, we apply Theorem 2 to get the output feedback controller. Denote $\underline{h}_{ij}(x_1) = \underline{w}_i(x_1)\underline{m}_j(x_1)$ and $\bar{h}_{ij}(x_1) = \bar{w}_i(x_1)\bar{m}_j(x_1)$. When the number of stairs of the staircase MFs is 5 and 10, respectively. By applying Theorem 2, we get the following results.

Case 1: when the number of stairs of the MFs is 5, the minimum $\ell_2 - \ell_\infty$ performance is $\gamma = 0.78$. The controller

parameters are listed as follows.

$$\begin{aligned} A_{c11} &= \begin{bmatrix} -1.3311 & -1.6743 \\ -1.3820 & -0.4602 \end{bmatrix} \\ A_{c12} &= \begin{bmatrix} -1.3364 & -1.7062 \\ -1.3997 & -0.4710 \end{bmatrix}, \\ A_{c21} &= \begin{bmatrix} -0.1351 & -0.3914 \\ -0.3138 & 0.5952 \end{bmatrix} \\ A_{c22} &= \begin{bmatrix} -0.1350 & -0.3956 \\ -0.3207 & 0.5828 \end{bmatrix}, \\ B_{c1} &= \begin{bmatrix} 1.1458 \\ 1.9655 \end{bmatrix}, B_{c2} = \begin{bmatrix} 1.1383 \\ 1.9947 \end{bmatrix}, \\ C_{c1} &= \begin{bmatrix} -1.0483 & -1.1715 \end{bmatrix} \\ C_{c2} &= \begin{bmatrix} -1.0537 & -1.1924 \end{bmatrix}, \end{aligned}$$

Case 2: when the number of stairs of the MFs is 10, the minimum $\ell_2 - \ell_\infty$ performance is $\gamma = 0.66$. The controller parameters listed are as follows.

$$\begin{aligned} A_{c11} &= \begin{bmatrix} -1.6589 & -1.8853 \\ -1.4080 & -0.4959 \end{bmatrix}, \\ A_{c12} &= \begin{bmatrix} -1.6638 & -1.9191 \\ -1.3740 & -0.4863 \end{bmatrix}, \\ A_{c21} &= \begin{bmatrix} -0.2001 & -0.4319 \\ -0.3619 & 0.5579 \end{bmatrix}, \\ A_{c22} &= \begin{bmatrix} -0.1988 & -0.4363 \\ -0.3511 & 0.5645 \end{bmatrix}, \\ B_{c1} &= \begin{bmatrix} 1.4533 \\ 2.3983 \end{bmatrix}, B_{c2} = \begin{bmatrix} 1.4458 \\ 2.3407 \end{bmatrix}, \\ C_{c1} &= \begin{bmatrix} -1.0162 & -1.0662 \end{bmatrix} \\ C_{c2} &= \begin{bmatrix} -1.0157 & -1.0814 \end{bmatrix}, \end{aligned}$$

To demonstrate the simulation results graphically, taking the case of $\hat{k} = 10$ as an example, Fig. 2 shows its upper and lower MFs and its corresponding approximate staircase MFs. Fig. 3 shows the corresponding responses of system states.

Fig. 2. The lower and upper MFs and its staircase MFs approximation.

Fig. 3. The system state and output signals under the controller (4).

Fig. 4. The system state and output signals under the controller (4) by membership-functions-independent condition.

Simulation results show that the system is successfully stabilized by using Theorem 2. Besides, the increase of approximation degree (which is reflected by the number of staircases) of approximation MFs to the upper and lower bound MFs can improve the $\ell_2 - \ell_\infty$ performance of IT2 fuzzy controller, which is reasonable. To obtain the minimum γ in Algorithm 1, one can process a linear search of γ . The value of $\mathcal{M}$ can generally be taken as a relatively large value, but this will also increase the computational burden. From Theorem 2, we can easily get a membership-functions-independent (MFI) condition: Consider state-delay IT2 FMB control system (3), it is asymptotically stable with a $\ell_2 - \ell_\infty$ performance index γ if there exist matrices $\mathcal{P} > 0$, $\mathcal{L} > 0$, $\mathcal{G}$, $\mathcal{J}$, $\mathcal{A}_{ij}$, $\mathcal{B}_j$, $\mathcal{C}_j$, $\mathcal{Q} > 0$, $\mathcal{Q} > 0$, $\hat{R}_1^g$, $\hat{R}_2^g$ with $i = 1, 2, \dots, n_p$, $j = 1, 2, \dots, n_c$, $g = 1, 2, 3$, satisfying $\tilde{\Upsilon}_{ij1} < 0$, $\tilde{\Upsilon}_{ij2} < 0$, $\mathcal{Q}\mathcal{Q} = I$. Through the CCL process similar to Algorithm 1, the controller can be obtained same as (28)-(31). The controller parameters obtained by corresponding MFI approach are shown as follows:

$$\begin{aligned} A_{c11} &= A_{c12} \begin{bmatrix} -1.0070 & -1.1899 \\ -1.2180 & -0.3320 \end{bmatrix} \\ A_{c21} &= A_{c22} \begin{bmatrix} -0.0896 & -0.3014 \\ -0.2167 & 0.7609 \end{bmatrix} \\ B_{c1} &= B_{c2} \begin{bmatrix} 1.1668 \\ 1.4949 \end{bmatrix}, \\ C_{c1} &= C_{c2} \begin{bmatrix} -0.8757 & -0.9776 \end{bmatrix}. \end{aligned}$$

Fig. 4 shows the controlled system states obtained by membership-functions-independent condition. Table IV compares the minimum performance indexes γ achieved by several methods.

TABLE IV
OBTAINED MINIMUM γ BY DIFFERENT $\hat{k}$ OR APPROACHES

Theorem 2 with $\hat{k} = 10$	Theorem 2 with $\hat{k} = 5$	membership-independent approach
$\gamma_{min} = 0.66$	$\gamma_{min} = 0.78$	$\gamma_{min} = 1.02$

V. CONCLUSION

This paper focus on the design of $\ell_2 - \ell_\infty$ DOF controller for state-delay nonlinear systems via IT2 FMB systems. Though the analysis for the augmented closed-loop state-delay IT2 FMB control system, the LMI-based delay-dependent stability condition is obtained. The analysis of time delay term benefits from the application of Wirtinger-based inequality. Benefit by convex linearization method and projection theorem, a method of DOF controller design satisfying $\ell_2 - \ell_\infty$ performance is obtained. A MFD method based on staircase MFs is introduced to relax the condition. Simulation results demonstrate that the controller designed in this paper can stabilize the system successfully and the MFD technique can achieve a lower $\ell_2 - \ell_\infty$ performance index.

REFERENCES

- [1] T. Takagi and M. Sugeno, "Fuzzy identification of systems and its applications to modeling and control," in *Readings in fuzzy sets for intelligent systems*. Elsevier, 1993, pp. 387–403.
- [2] L. Wu and W. X. Zheng, " $\ell_2 - \ell_\infty$ control of nonlinear fuzzy itô stochastic delay systems via dynamic output feedback," *IEEE Transactions on Systems, Man, and Cybernetics, Part B (Cybernetics)*, vol. 39, no. 5, pp. 1308–1315, 2009.
- [3] X. Su, L. Wu, P. Shi, and Y.-D. Song, "A novel approach to output feedback control of fuzzy stochastic systems," *Automatica*, vol. 50, no. 12, pp. 3268–3275, 2014.
- [4] T. Haidegger, L. Kovács, S. Preitl, R. Precup, B. Benyo, and Z. Benyo, "Controller design solutions for long distance telesurgical applications," *International Journal of Artificial Intelligence*, vol. 6, no. S11, pp. 48–71, 2011.
- [5] R. Precup, M. L. Tomescu, and S. Preitl, "Lorenz system stabilization using fuzzy controllers," *International Journal of Computers Communications & Control*, vol. 2, no. 3, pp. 279–287, 2007.
- [6] R. Precup and M. L. Tomescu, "Stable fuzzy logic control of a general class of chaotic systems," *Neural Computing and Applications*, vol. 26, no. 3, pp. 541–550, 2015.
- [7] Z. Chen, Z. Li, and C. L. P. Chen, "Disturbance observer-based fuzzy control of uncertain mimo mechanical systems with input nonlinearities and its application to robotic exoskeleton," *IEEE Transactions on Systems, Man, and Cybernetics*, vol. 47, no. 4, pp. 984–994, 2017.
- [8] J. A. Medacampana, A. Grandemeza, J. D. J. Rubio, R. Tapiaherrera, T. Hernandezcortes, A. V. Curtidorlopez, L. A. Paramocarranza, and I. O. Cazaesramirez, "Design of stabilizers and observers for a class of multivariable tcs fuzzy models on the basis of new interpolation

- functions,” *IEEE Transactions on Fuzzy Systems*, vol. 26, no. 5, pp. 2649–2662, 2018.
- [9] H. K. Lam and L. Seneviratne, “Tracking control of sampled-data fuzzy-model-based control systems,” *IET Control Theory & Applications*, vol. 3, no. 1, pp. 56–67, 2009.
 - [10] H. Li, X. Jing, H. K. Lam, and P. Shi, “Fuzzy sampled-data control for uncertain vehicle suspension systems,” *IEEE Transactions on Cybernetics*, vol. 44, no. 7, pp. 1111–1126, 2013.
 - [11] H. K. Lam and M. Narimani, “Quadratic-stability analysis of fuzzy-model-based control systems using staircase membership functions,” *IEEE Transactions on Fuzzy Systems*, vol. 18, no. 1, pp. 125–137, 2009.
 - [12] H. K. Lam, “LMI-based stability analysis for fuzzy-model-based control systems using artificial T-S fuzzy model,” *IEEE Transactions on Fuzzy Systems*, vol. 19, no. 3, pp. 505–513, 2011.
 - [13] L. Wu, X. Su, P. Shi, and J. Qiu, “A new approach to stability analysis and stabilization of discrete-time ts fuzzy time-varying delay systems,” *IEEE Transactions on Systems, Man, and Cybernetics, Part B (Cybernetics)*, vol. 41, no. 1, pp. 273–286, 2010.
 - [14] K. Cao, X. Gao, H. K. Lam, A. Vasilakos, and W. Pedrycz, “A new relaxed stability condition for takagi-sugeno fuzzy control systems using quadratic fuzzy lyapunov functions and staircase membership functions,” *Int. J. Fuzzy Syst.*, vol. 16, no. 3, pp. 327–337, 2014.
 - [15] H. K. Lam and F. H. Leung, “Sampled-data fuzzy controller for time-delay nonlinear systems: fuzzy-model-based lmi approach,” *IEEE Transactions on Systems, Man, and Cybernetics, Part B (Cybernetics)*, vol. 37, no. 3, pp. 617–629, 2007.
 - [16] X. Su, P. Shi, L. Wu, and Y.-D. Song, “A novel approach to filter design for t-s fuzzy discrete-time systems with time-varying delay,” *IEEE Transactions on Fuzzy Systems*, vol. 20, no. 6, pp. 1114–1129, 2012.
 - [17] X. Su, P. Shi, L. Wu, and M. V. Basin, “Reliable filtering with strict dissipativity for ts fuzzy time-delay systems,” *IEEE Transactions on Cybernetics*, vol. 44, no. 12, pp. 2470–2483, 2014.
 - [18] H. K. Lam, H. Li, C. Deters, E. L. Secco, H. A. Wurdemann, and K. Althoefer, “Control design for interval type-2 fuzzy systems under imperfect premise matching,” *IEEE Transactions on Industrial Electronics*, vol. 61, no. 2, pp. 956–968, 2013.
 - [19] H. K. Lam and L. D. Seneviratne, “Stability analysis of interval type-2 fuzzy-model-based control systems,” *IEEE Transactions on Systems, Man, and Cybernetics, Part B (Cybernetics)*, vol. 38, no. 3, pp. 617–628, 2008.
 - [20] H. K. Lam and M. Narimani, “Stability analysis and performance design for fuzzy-model-based control system under imperfect premise matching,” *IEEE Transactions on Fuzzy Systems*, vol. 17, no. 4, pp. 949–961, 2009.
 - [21] H. Li, X. Sun, L. Wu, and H. K. Lam, “State and output feedback control of interval type-2 fuzzy systems with mismatched membership functions,” *IEEE Transactions on Fuzzy Systems*, vol. 23, no. 6, pp. 1943–1957, 2015.
 - [22] H. Li, C. Wu, L. Wu, H. K. Lam, and Y. Gao, “Filtering of interval type-2 fuzzy systems with intermittent measurements,” *IEEE transactions on cybernetics*, vol. 46, no. 3, pp. 668–678, 2015.
 - [23] J. Liu, C. Wu, Z. Wang, and L. Wu, “Reliable filter design for sensor networks using type-2 fuzzy framework,” *IEEE Transactions on Industrial Informatics*, vol. 13, no. 4, pp. 1742–1752, 2017.
 - [24] Y. Zeng, H. K. Lam, and L. Wu, “Model reduction of discrete-time interval type-2 t-s fuzzy systems,” *IEEE Transactions on Fuzzy Systems*, vol. 26, no. 6, pp. 3545–3554, 2018.
 - [25] B. Xiao, H. K. Lam, and H. Li, “Stabilization of interval type-2 polynomial-fuzzy-model-based control systems,” *IEEE Transactions on Fuzzy Systems*, vol. 25, no. 1, pp. 205–217, 2016.
 - [26] B. Xiao, H. K. Lam, G. Song, and H. Li, “Output-feedback tracking control for interval type-2 polynomial fuzzy-model-based control systems,” *Neurocomputing*, vol. 242, pp. 83–95, 2017.
 - [27] B. Xiao, H. K. Lam, X. Yang, Y. Yu, and H. Ren, “Tracking control design of interval type-2 polynomial-fuzzy-model-based systems with time-varying delay,” *Engineering Applications of Artificial Intelligence*, vol. 75, pp. 76–87, 2018.
 - [28] X. Yang, H. K. Lam, and L. Wu, “Membership-dependent stability conditions for type-1 and interval type-2 t-s fuzzy systems,” *Fuzzy Sets and Systems*, vol. 356, pp. 44–62, 2019.
 - [29] H. K. Lam, “A review on stability analysis of continuous-time fuzzy-model-based control systems: From membership-function-independent to membership-function-dependent analysis,” *Engineering Applications of Artificial Intelligence*, vol. 67, pp. 390–408, 2018.
 - [30] R. Martínez, O. Castillo, and L. T. Aguilar, “Optimization of interval type-2 fuzzy logic controllers for a perturbed autonomous wheeled mobile robot using genetic algorithms,” *Information Sciences*, vol. 179, no. 13, pp. 2158–2174, 2009.
 - [31] C.-J. Kim and D. Chwa, “Obstacle avoidance method for wheeled mobile robots using interval type-2 fuzzy neural network,” *IEEE Transactions on Fuzzy Systems*, vol. 23, no. 3, pp. 677–687, 2014.
 - [32] M. A. Sanchez, O. Castillo, and J. R. Castro, “Generalized type-2 fuzzy systems for controlling a mobile robot and a performance comparison with interval type-2 and type-1 fuzzy systems,” *Expert Systems with Applications*, vol. 42, no. 14, pp. 5904–5914, 2015.
 - [33] H. M. Yassin, H. H. Hanafy, and M. M. Hallouda, “Enhancement low-voltage ride through capability of permanent magnet synchronous generator-based wind turbines using interval type-2 fuzzy control,” *IET Renewable Power Generation*, vol. 10, no. 3, pp. 339–348, 2016.
 - [34] Z. Hu, S. Liu, L. Yang, and L. Wu, “Distributed fuzzy filtering for load frequency control of non-linear interconnected power systems under cyber-physical attacks,” *IET Control Theory Applications*, vol. 14, no. 4, pp. 527–538, 2020.
 - [35] L. Sheng and X. Ma, “Stability analysis and controller design of interval type-2 fuzzy systems with time delay,” *International Journal of systems science*, vol. 45, no. 5, pp. 977–993, 2014.
 - [36] H. Li, J. Wang, L. Wu, H. K. Lam, and Y. Gao, “Optimal guaranteed cost sliding-mode control of interval type-2 fuzzy time-delay systems,” *IEEE Transactions on Fuzzy Systems*, vol. 26, no. 1, pp. 246–257, 2017.
 - [37] Y. Li, H. K. Lam, L. Zhang, H. Li, F. Liu, and S.-H. Tsai, “Interval type-2 fuzzy-model-based control design for time-delay systems under imperfect premise matching,” in *2015 IEEE International Conference on Fuzzy Systems (FUZZ-IEEE)*. IEEE, 2015, pp. 1–6.
 - [38] H. Hassani, J. Zarei, M. Chadli, and J. Qiu, “Unknown input observer design for interval type-2 t-s fuzzy systems with immeasurable premise variables,” *IEEE transactions on cybernetics*, vol. 47, no. 9, pp. 2639–2650, 2016.
 - [39] T. Zhao and S. Dian, “State feedback control for interval type-2 fuzzy systems with time-varying delay and unreliable communication links,” *IEEE Transactions on Fuzzy Systems*, vol. 26, no. 2, pp. 951–966, 2017.
 - [40] P. T. Nam, P. N. Pathirana, and H. Trinh, “Discrete wirtinger-based inequality and its application,” *Journal of the Franklin Institute*, vol. 352, no. 5, pp. 1893–1905, 2015.
 - [41] C. Zhang, Y. He, L. Jiang, M. Wu, and H. Zeng, “Delay-variation-dependent stability of delayed discrete-time systems,” *IEEE Transactions on Automatic Control*, vol. 61, no. 9, pp. 2663–2669, 2016.
 - [42] A. Seuret, F. Gouaisbaut, and E. Fridman, “Stability of discrete-time systems with time-varying delays via a novel summation inequality,” *IEEE Transactions on Automatic Control*, vol. 60, no. 10, pp. 2740–2745, 2015.
 - [43] X.-L. Zhu and G.-H. Yang, “Jensen inequality approach to stability analysis of discrete-time systems with time-varying delay,” in *2008 American Control Conference*. IEEE, 2008, pp. 1644–1649.
 - [44] H. Li, C. Wu, S. Yin, and H. Lam, “Observer-based fuzzy control for nonlinear networked systems under unmeasurable premise variables,” *IEEE Transactions on Fuzzy Systems*, vol. 24, no. 5, pp. 1233–1245, 2016.
 - [45] H. Li, J. Wang, L. Wu, H. Lam, and Y. Gao, “Optimal guaranteed cost sliding-mode control of interval type-2 fuzzy time-delay systems,” *IEEE Transactions on Fuzzy Systems*, vol. 26, no. 1, pp. 246–257, 2018.

Yi Zeng was born in Heilongjiang, China in 1991. He received the B.E. degree and M.E degree in control science and control engineering from Harbin Institute of Technology, Harbin, China, in 2014 and 2016, respectively. He is currently working toward the Ph.D. degree at King’s College London, London, United Kingdom.

His current research interests include fuzzy control theory, model reduction, robust control theory and stochastic systems.

Hak-Keung Lam (M'98-SM'10-F'20) received the B.Eng. (Hons.) and Ph.D. degrees from the Department of Electronic and Information Engineering, The Hong Kong Polytechnic University, Hong Kong, in 1995 and 2000, respectively.

From 2000 to 2005, he was with the Department of Electronic and Information Engineering at The Hong Kong Polytechnic University as Post-Doctoral Fellow and Research Fellow respectively. He joined Kings College London in 2005 as a Lecturer and is currently a Reader. He is the co-editor for two edited

volumes entitled *Control of Chaotic Nonlinear Circuits* (World Scientific, 2009) and *Computational Intelligence and Its Applications* (World Scientific, 2012), and authored/coauthored the monographs entitled *Stability Analysis of Fuzzy-Model-Based Control Systems* (Springer, 2011), *Polynomial Fuzzy Model-Based Control Systems* (Springer, 2016), and *Analysis and Synthesis for IT2 Fuzzy-Model-Based Systems* (Springer, 2016). His current research interests include intelligent control systems and computational intelligence.

Dr. Lam is an associate editor of IEEE TRANSACTIONS ON FUZZY SYSTEMS, IEEE TRANSACTIONS ON CIRCUITS AND SYSTEMS II: EXPRESS BRIEFS, *IET Control Theory and Applications*, *International Journal of Fuzzy Systems*, *Neurocomputing* and *Nonlinear Dynamics*, a guest editor and an editorial board member for various international journals, a reviewer for many journals, a special session organiser for a number of sessions, and a program committee member for various international conferences.

Ligang Wu (M10CSM12CF20) received the B.S. degree in Automation from Harbin University of Science and Technology, China in 2001; the M.E. degree in Navigation Guidance and Control from Harbin Institute of Technology, China in 2003; the PhD degree in Control Theory and Control Engineering from Harbin Institute of Technology, China in 2006. From January 2006 to April 2007, he was a Research Associate in the Department of Mechanical Engineering, The University of Hong Kong, Hong Kong. From September 2007 to June 2008, he was a

Senior Research Associate in the Department of Mathematics, City University of Hong Kong, Hong Kong. From December 2012 to December 2013, he was a Research Associate in the Department of Electrical and Electronic Engineering, Imperial College London, London, UK. In 2008, he joined the Harbin Institute of Technology, China, as an Associate Professor, and was then promoted to a Full Professor in 2012. Prof. Wu was the winner of the National Science Fund for Distinguished Young Scholars in 2015, and received China Young Five Four Medal in 2016. He was named as the Distinguished Professor of Chang Jiang Scholar in 2017, and was named as the Highly Cited Researcher since 2015.

Prof. Wu currently serves as an Associate Editor for a number of journals, including IEEE TRANSACTIONS ON AUTOMATIC CONTROL, IEEE TRANSACTIONS ON INDUSTRIAL ELECTRONICS, IEEE/ASME TRANSACTIONS ON MECHATRONICS, *Information Sciences*, *Signal Processing*, and *IET Control Theory and Applications*. He is also an Associate Editor for the Conference Editorial Board, IEEE Control Systems Society. Prof. Wu has published 7 research monographs and more than 170 research papers in international referred journals. His current research interests include switched systems, stochastic systems, computational and intelligent systems, sliding mode control, and advanced control techniques for power electronic systems.

Bo Xiao received Ph.D. degree from the Department of Informatics, King's College London, U.K. in 2018. He is currently a research associate with the Hamlyn Centre for Robotic Surgery and the Department of Computing, Imperial College London, U.K. During the period 2017 to 2018, he worked as a research fellow at Advanced Robotics Centre and the Department of Biomedical Engineering, National University of Singapore, Singapore.

His current research interests include fuzzy model based control systems, interval type-2 fuzzy logic, polynomial control systems, machining learning, reinforcement learning and their applications in medical robotics.

He has been the guest editor for *IEEE Transactions on Fuzzy Systems* and *IET Control Theory and Applications*. He has served as an active reviewer for a number of peer-reviewed journals including *IEEE Transactions on Fuzzy Systems*, *IEEE Transactions on Automatic Control*, *IEEE Transactions on Cybernetics*, *Fuzzy Sets and Systems* and *IET Control Theory and Applications*.