



## King's Research Portal

### *Document Version*

Early version, also known as pre-print

[Link to publication record in King's Research Portal](#)

### *Citation for published version (APA):*

Charlton, P. H., Bonnici, T. A., Tarassenko, L., Watkinson, P., Beale, R., Clifton, D. A., & Alastruey-Armon, J. (2018). A Signal Quality Index for the Impedance Respiratory Signal. In *BioMedEng 2018 Conference*

### **Citing this paper**

Please note that where the full-text provided on King's Research Portal is the Author Accepted Manuscript or Post-Print version this may differ from the final Published version. If citing, it is advised that you check and use the publisher's definitive version for pagination, volume/issue, and date of publication details. And where the final published version is provided on the Research Portal, if citing you are again advised to check the publisher's website for any subsequent corrections.

### **General rights**

Copyright and moral rights for the publications made accessible in the Research Portal are retained by the authors and/or other copyright owners and it is a condition of accessing publications that users recognize and abide by the legal requirements associated with these rights.

- Users may download and print one copy of any publication from the Research Portal for the purpose of private study or research.
- You may not further distribute the material or use it for any profit-making activity or commercial gain
- You may freely distribute the URL identifying the publication in the Research Portal

### **Take down policy**

If you believe that this document breaches copyright please contact [librarypure@kcl.ac.uk](mailto:librarypure@kcl.ac.uk) providing details, and we will remove access to the work immediately and investigate your claim.

# BioMedEng18

## A Signal Quality Index for the Impedance Respiratory Signal

**P. H. Charlton<sup>1,2</sup>**, T. Bonnici<sup>3</sup>, L. Tarassenko<sup>2</sup>, P. J. Watkinson<sup>4</sup>, R. Beale<sup>3</sup>, D. A. Clifton<sup>2</sup>, J. Alastruey<sup>1</sup>

<sup>1</sup>Department of Biomedical Engineering, King's College London, King's Health Partners, London, SE1 7EH

<sup>2</sup>Department of Engineering Science, University of Oxford, Oxford OX3 7DQ

<sup>3</sup>Department of Asthma, Allergy and Lung Biology, King's College London, King's Health Partners, London, SE1 7EH

<sup>4</sup>Kadoorie Centre for Critical Care Research and Education, Oxford University Hospitals NHS FT, Oxford, OX3 9DU

### Introduction

Respiratory rate (RR) is an important physiological marker, often increasing prior to acute clinical deteriorations such as cardiac arrests. Consequently, RR is often monitored using thoracic impedance pneumography (IP), since the IP signal can be easily acquired with ECG electrodes. However, IP is highly susceptible to motion artifact, reducing signal quality and resulting in inaccurate RRs. Our aim was to design a signal quality index (SQI) to discriminate between low and high quality periods of IP, and to estimate RR accurately from high quality periods.

### Methods

We designed an SQI to quality assess segments of IP of 32 seconds, based on [1]. It consists of: (i) filtering the IP signal to eliminate non-respiratory frequencies; (ii) detecting individual breaths; (iii) assessing the plausibility of breath-to-breath timings; and (iv) assessing the similarity of breath morphologies using template matching. Performance was assessed using IP signals from 59 hospital patients recovering from cardiac surgery, each of one hour duration. Each segment was manually annotated as high or low quality, and individual breaths were annotated. Performance was compared to an existing SQI [2], and the RRs provided by the clinical monitor.

### Results & Discussion

See table. The novel SQI had improved discriminatory performance compared to a technique from the literature [2]. RRs had a lower mean absolute error, more accurate estimates (error < 2 bpm), and fewer inaccurate estimates (error > 5 bpm), than this technique or the clinical monitor.

Performance metric	Novel SQI	Technique from literature	Monitor
SQI Sensitivity [%]	76.7	45.0	-
SQI Specificity [%]	84.9	77.4	-
Mean absolute error of RRs [bpm]	0.20	1.34	1.27
Proportion RR error < 2 bpm [%]	97.8	79.5	83.0
Proportion RR error > 5 bpm [%]	0.0	4.7	4.7

### Conclusion

The novel SQI can be used to improve the accuracy of RRs estimated from IP. It has applications in both tethered and wearable monitors, and in hospital and home settings.

### References

1. Orphanidou C *et al.* *IEEE J Biomed Health Inform.* 2015; 19(3): 832-8.
2. Pimentel M A F, Charlton P H, Clifton D A. in *Wearable Electronics Sensors.* 2015; 15: 241-62

### Acknowledgments

This work was supported by the Engineering and Physical Sciences Research Council (EPSRC) [EP/H019944/1] and the Wellcome/EPSRC Centre for Medical Engineering [WT 203148/Z/16/Z].